



## Merlin Stealth M28S

### Features

- 7.6 Joule output energy (two-zone)
- Robust and flexible design for home, commercial and industrial security
- Can be expanded into a multi-zone system
- Built-in alarm monitors tampering or faults on the high voltage and earth fence wires
- Connectable to armed response radio or GSM module
- Lightning and power surge protection
- Intelligent power saving to extend battery life

- Easy-to-use tag included for controlling the energizer
- Optional keypad for controlling and programming the energizer. This allows the user to control the energizer remotely, with up to four keypads
- Powered by 240V mains and includes built-in battery for back-up power
- Two built-in gate alarm inputs to monitor if the gates are open or closed

### **Specifications**

Enclosure size: L370 x W232 x D145

Weight excluding battery (7AH): 4.8kg

Weight including battery (7AH): 7.0kg

IP rating: IPx4

Operating temperatures: -10°C to 50°C

Operating humidity: < 80% non-condensing

Electrical supply voltage: 240V

Typical power consumption (normal operating conditions): 27VA

Standby time (fully charged battery): 6hrs

Energy output 500 Ohms load 7.6 Joule

Open circuit voltage 9 300V

**Get A Quote**

➡  **084 704 2661**

☐ **dheran@spacesat.co.za**

**<https://www.spacesec.co.za/contact-us/>**