



Merlin Stealth Master

Features

- 7.6 Joule output energy (two-zone)
- Up to nine extra two-zone Merlin Stealth energizers can be connected into a 20 zone system.
- The system is controlled by the 20-zone LED keypad
- Robust and flexible design for home, commercial and industrial security
- Built-in alarm monitors tampering or faults on the high voltage and earth fence wires
- Connectable to armed response radio or GSM module
- Lightning and power surge protection
- Intelligent power saving to extend battery life
- Easy-to-use tag included for controlling the energizer
- Powered by 240V mains and includes built-in battery for back-up power
- Two built-in gate alarm inputs to monitor if the gates are open or closed

Specifications

Enclosure size: L370 x W232 x D145

Weight excluding battery (7AH): 4.8kg

Weight including battery (7AH): 7.0kg

IP rating: IPx4

Operating temperatures: -10°C to 50°C

Operating humidity: < 80% non-condensing

Electrical supply voltage: 240V

Typical power consumption (normal operating conditions): 27VA

Standby time (fully charged battery): 6hrs

Energy output 500 Ohms load 7.6 Joule

Open circuit voltage 9 300V

Get A Quote

➔  **084 704 2661**

☐ **dheran@spacesat.co.za**

<https://www.spacesec.co.za/contact-us/>